

J3500P18 3400-3600 MHz 18 dBi V-POL or H-POL Patch Antenna



Antenna Model No.	J3500P18
Frequency Range	3400 - 3600 MHz
Bandwidth	200 MHz
Gain	18 dBi
Horizontal Beamwidth	17°
Vertical Beamwidth	17°
Front-to-Back Ratio	≥ 28 dB
VSWR	≤ 2.0
Nominal Impedance	50 Ohms
Maximum Power	100 Watts
Polarization	Vertical or Horizontal
Connector	N Female
Dimensions	12.0" x 12.0" x 1.3" / 305 x 305 x 32 mm
Weight	4.4 lbs / 2.0 kg
Wind Load	120 mph / 60 m/s
Radome	ABS
Mast Mount Diameter	1.6" - 2.0" / 40 - 50 mm
Operating Temperature	-22°F to 140°F / -30°C to 60°C
Mounting Options	Mast Mount

